



# Power generator F 3001 iS

Nr art. 32628

## Characteristic

- Stable frequency 50 Hz
- Inverter technology
- Voltage stabilization  $\pm 1\%$
- Low level of THD  $\leq 3\%$
- Supersilent 91 dB(A)
- Weight only 25 kg
- Fuel saving function reduce engine speed at low load
- Possibility of synchronization two units F 3001 iS
- Battery charger

## Technical parameters

<b>Frequency</b>	<b>50 Hz</b>
<b>Voltage</b>	<b>230 V</b>
<b>Maximum power</b>	<b>2,5 kW</b>
<b>Nominal power</b>	<b>2,3 kW</b>
<b>Prime current</b>	<b>10 A</b>
Engine	Rato
Model	R 120-Vi
Capacity	122 cm <sup>3</sup>
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	0,38 L
Starting system	Manual
Fuel	Petrol
Fuel tank	4,5 L
Consumption (load 50/100%)	0,9 / 1,5 L / h
Noise level Lwa	91 dB(A)
Weight	25 kg
Length	520 mm
Width	320 mm
Height	460 mm

## Standard equipment

- 2 Socket 230 V 16 A
- USB Socket
- Socket and cables for battery charging 12 V 8,3 A
- Overload signalization
- Overload protection
- Low oil warning diode

## Optional and service equipment

- Exhaust hose Nr art. 15876
- Exhaust adapter Nr art. 37087
- Synchronization cables for two generators F3001 iS Nr art. 26790
- Service kit (air filter, spark plug, engine oil) Nr art. 33634

## Norms and Directives

- **2000/14/WE**  
Noise Directive 2005/88/WE
- **2006/42/WE**  
Machinery Directive
- **2014/35/UE**  
Low Voltage Directive
- **2014/30/UE**  
EC Directive