



## Power generator

# F 8000 TRA

Nr art. 35588

### Characteristic

- Cyfrowa regulacja napięcia  $\pm 1,5\%$  na każdej fazie
- Low level of THD  $\leq 6\%$
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP 23
- Autonomy (at 75 % load) 15,5h
- Ready for manual and automatic operation

### Technical parameters

<b>Frequency</b>	<b>50 Hz</b>
<b>Voltage</b>	<b>400 / 230 V</b>
<b>Power 3~ max / nom.</b>	<b>7,7 kVA / 7,0 kVA (cos <math>\phi</math> 0,8)</b>
<b>Prime current 3~</b>	<b>10,1 A</b>
<b>Power 1~ max / nom.</b>	<b>3,9 kW / 3,5 kW</b>
<b>Prime current 1~</b>	<b>15,2 A</b>

Engine	Rato
Model	R 420
Capacity	420 cm <sup>3</sup>
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	1,1 L
Starting system	Manual + electric
Fuel	Petrol
Fuel tank	45 L
Consumption (load 75%)	2,9L / h
Noise level Lwa	99 dB(A) do zabudowy

Weight	95 kg
Length	790 mm
Width	580 mm
Height	650 mm

### Standard equipment

- AVR
- Socket 400 V 16 A
- Socket 230 V 16 A
- Overload protection
- Oil level sensor
- Silencer with exhaust adapter
- Battery
- Connection for ATS panel

### Optional and service equipment

- Exhaust hose
  - Hourmeter
  - Transportation set
  - Service kit
  - Service kit (air filter, spark plug, engine oil)
  - ATS panel
- Nr art. 15876  
Nr art. 23300  
Nr art. 34995  
Nr art. 35447  
Nr art. 30312

### Norms and Directives

- **2006/42/WE**  
Machinery Directive
- **2014/35/UE**  
Low Voltage Directive
- **2014/30/UE**  
EC Directive