



Power generator

F 5001 R

Nr art. 36102

Characteristic

- Regulacja napięcia $\pm 2\%$
- Low level of THD $\leq 6\%$
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP 23

Technical parameters

50 Hz
230 V
4,0 kW
3,6 kW
15,7 A

Rato
R300
301 cm³
Air
1
4
1,1 L
Manual
Petrol
5,4 L
2,2 L / h
97 dB(A)

53 kg
650 mm
520 mm
490 mm

Standard equipment

- AVR
- 2 sockets 230 V 16 A
- Overload protection
- Oil level sensor

Optional and service equipment

- Service kit
(air filter, spark plug, engine oil) Nr art. 35110

Norms and Directives

- **2000/14/WE**
Noise Directive 2005/88/WE
- **2006/42/WE**
Machinery Directive
- **2014/35/UE**
Low Voltage Directive
- **2014/30/UE**
EC Directive