



Power generator

FH 7541

Nr art. 37056

Characteristic

- Voltage stabilization ± 5 -10 %
- Low level of THD ≤ 4 %
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP 54
- Odbiór pełnej mocy agregatu z jednego gniazda 32 A 3P IP 67

Technical parameters

Frequency	50 Hz
Voltage	230 V
Maximum power	6,2 kW
Nominal power	5,6 kW
Prime current	24,3 A
Engine	Honda
Model	GX 390
Capacity	389 cm ³
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	1,1 L
Starting system	Manual
Fuel	Petrol
Fuel tank	6,1 L
Consumption (load 50/100%)	2,7 L / h
Noise level Lwa	97 dB(A)
Weight	96 kg
Length	745 mm
Width	530 mm
Height	495 mm

Standard equipment

- Socket 230 V 16 A IP 67
- Socket 230 V 16 A 3P IP 67
- Socket 230 V 32 A 3P IP 67
- Overload protection
- Oil level sensor
- Hourmeter

Optional and service equipment

- Exhaust hose Nr art. 15876
- Exhaust adapter Nr art. 10118
- Service kit (air filter, spark plug, engine oil) Nr art. 16582

Norms and Directives

- **2000/14/WE**
Noise Directive 2005/88/WE
- **2006/42/WE**
Machinery Directive
- **2014/35/UE**
Low Voltage Directive
- **2014/30/UE**
EC Directive